

BALDOR® • RELIANCE

Product Information Packet

GCP24114

.025HP,1400RPM,1PH,50/60HZ,PSSH-0,2412C

Part Detail							
Revision:	R	Status:	PRD/A	Change #:		Proprietary:	No
Type:	AC	Prod. Type:	2412C	Elec. Spec:	24WGW010	CD Diagram:	CD1018
Enclosure:	TENV	Mfg Plant:		Mech. Spec:		Layout:	24LYE232
Frame:	PSSH	Mounting:		Poles:	04	Created Date:	
Base:		Rotation:	R	Insulation:	F	Eff. Date:	05-22-2015
Leads:	3#18					Replaced By:	
Literature:		Elec. Diagram:					

Nameplate NP1220A05

CAT.NO.	GCP24114		
SER.NO			
SPEC.	24E232W010G1		
HP	.025	TE	
VOLTS	115		
AMP	.79//.56		
HZ	50//60	PH	1
AMB.	40	DUTY	CONT
CAP	8	CODE	-
SER.F.	1.00	CLASS	F
SF AMP	-		
R.P.M.	7.6//9.4		
TORQ/IN LB	120		
RATIO	180:1		
APRV-CE		APRV-CSA	
		APRV-UL	

Parts List		
Part Number	Description	Quantity
SA078356	SA 24E232W010G1	1.000 EA
RA071845	RA 24E232W010G1	1.000 EA
OC4008A02	DRY FILM METALLIZED CAP,8MFD 250V	1.000 EA
LC0895	CONN.DIAGRAM 1PH,SINGLE VOLT,TYPE PSC	1.000 EA
HG0046A01BG	HSG,PSSH EP STD 24 FR. AC MOUNTING	1.000 EA
BMH1729	WASHER,PREC 1.020"X.628"X.020"	1.000 EA
HW5002A42	N5002-102 RET RING INTERNBEVELED F/6000	1.000 EA
HW3064E05	1/8 X 1/2 PIN DRIVE LOK TYPE H	1.000 EA
HW4600G58	SEAL,10X20X4MM PGS 25002184 VITON VT802	1.000 EA
HA4021A05	1/16 NPSF-HX SOC PIPE PLUG TAPER DRY SEA	1.000 EA
24EP3100A05G	EP,24AC ODE CL NONE	1.000 EA
HW5109A08	WASHER, WAVE SPRING FOR 30MM BORE SMALLE	1.000 EA
55XT0632G03	6-32 X 0.187 RD HD PHILLIPS, SERRATED	1.000 EA
HA3199A82	THRU-BOLT PAN HEAD 8-32 X 5.125	2.000 EA
RM1020A21	O-RING,3.240 I.D. X .052 BUNA-N (NITRILE	1.000 EA
BH1163A02	SCE88 INA NEEDLE ROL SM21	1.000 EA
60XM0832A08	SCREW, PAN TORX 8-32X.500 THREAD FORMING	4.000 EA
HW4600C29	SEAL, TCM #0507416 SCW .50X.75X.165 RB	1.000 EA
MJ1000B02	KLUB. GH6-460 GEAR OIL 1 GALLON	0.030 GA
SG0047A03	SHAFT,ASSY PSSH LONG INT1 4RED 4.0/5.0	1.000 EA
SG0047A04	SHAFT,ASSY PSSH LONG INT2 4RED 3.0/4.0	1.000 EA
SG0047A05	SHAFT,ASSY PSSH LONG INT3 4RED 3.0/3.0	1.000 EA
SG0047A23	SHAFT,ASSY PSSH LONG OUTP 4RED 0.0/3.0	1.000 EA
CG0001A01BG	HSG,PSSH CAP STD 4 BORE MACH.	1.000 EA

Parts List (continued)		
Part Number	Description	Quantity
NP1220A05	NP,AC STD AD NONE V CE CSA UL GEAR MOTOR	1.000 EA
LB1451	WARNING LABEL, CE WARNING SYMBOLS ONLY	1.000 EA
MN416A01	TAG-INSTAL-MAINT no wire (1000/bx) 11/14	1.000 EA
CPA1000	PACKING GROUP STD. SINGLE	1.000 EA

Accessories		
Part Number	Description	Multiplier
BKP2400	CONDUIT BOX KIT FOR 24 FRAME	A8
LB73GR	"L" BRACKET KIT FOR PSSH GEARBOX-GRAY	A8
LB73	"L" BRACKET KIT FOR PSSH GEARBOX-BLACK	A8

No performance data has been
assigned to this product.



